EM Scattering

Homework assignment 2

Problem 1:

Consider a dielectric layer in free space. The layer has a relative dielectric constant of $\varepsilon_d=2.25$, is infinite, and is parallel to the x-y plane. A plane wave coming from below the layer hits it at an angle equal to θ_i . The polarization of the incident wave is either ${\sf TE}^{\sf z}$ where the electric field has no normal component (e.g., in the y-direction) or ${\sf TM}^{\sf z}$ where the magnetic field has no normal component. The frequency of the wave is $f=100{\rm GHz}$.

- 1. Plot the magnitude of the reflection coefficient as function of θ_i in both TE and TM cases when the layer is 1 mm-thick
- 2. Plot the magnitude of the reflection coefficient as function of θ_i in both TE and TM cases when the layer is 5 mm-thick

Problem 2:

A plane radio wave is incident on the ionosphere from the air. The relative dielectric constant of the ionosphere is $\varepsilon_d = 1 - \left(f_p / f \right)^2$ where f is the frequency of the wave and $f_p = 5 \mathrm{MHz}$ is the plasma frequency of the ionosphere. The ionosphere is assumed to be infinitely thick.

- 1. Compute the reflection coefficient for both TE and TM polarizations when the frequency of the wave is f = 3 MHz.
- 2. Repeat this calculation at the frequency of f = 6 MHz. Find the Brewster angle and the critical angle for total reflection.

Problem 3:

Consider the scalar wave equation $(\nabla^2 + k^2)\psi = 0$ in cylindrical coordinates, and a particular solution given by

$$\psi(\rho,\phi) = \exp(-jm\phi)J_m(k\rho)$$

where k is the wave number of the medium.

- 1. Find the corresponding $oldsymbol{M}$ and $oldsymbol{N}$ vectors
- 2. Sketch the real and imaginary parts of their components along the radial direction (as function of ρ) for m=1 and ϕ = 0
- 3. If these vectors are to represent an electric field how does the polarization change as function of radial distance ρ ? (Again take m=1 and ϕ = 0)

Problem 4:


We would like to solve the 2D, **scalar** scattering problem of a scalar wave incident upon an infinitely long circular cylinder whose radius is given by a and whose axis coincides with the z-axis. The incident wave is

$$\Psi_i(x, y) = A \exp(-jk_{i,x}x - jk_{i,y}y)$$

with $k_{i,x}^2 + k_{i,y}^2 = k^2$ where k is the wave number in the background medium. Like the incident wave, the scattered wave $\Psi_s(x,y)$ satisfies the 2D wave equation

$$\frac{\partial^2 \Psi_s}{\partial x^2} + \frac{\partial^2 \Psi_s}{\partial y^2} + k^2 \Psi_s = 0$$

- Using cylindrical coordinates, find the general solution of this equation in terms of a functional series. Take into account the behavior of the scattered wave at infinity.
- 2. The boundary condition on the surface of the cylinder is $\Psi=0$ in which $\Psi=\Psi_i+\Psi_s \text{ is the total field. Using this boundary condition, solve the scattering problem by determining the coefficients of the series found above.$



This document was created with Win2PDF available at http://www.win2pdf.com. The unregistered version of Win2PDF is for evaluation or non-commercial use only. This page will not be added after purchasing Win2PDF.